IMPROVEMENT OF POSITIONING ACCURACY USING MULTIPLE HOLE-AND-PIN SETS BASED ON MONTE CARLO SIMULATION

SHINYA SUZUKI[1], YUKI KAWAGUCHI[2], AKIMASA OTSUKA[3], TOHRU KANADA[1]

[1]College of Science and Engineering, Kanto Gakuin University, Yokohama, Japan

[2]Dentsu Soken, Inc., Tokyo, Japan

[3]Department of Mechanical Engineering, Sanyo-Onoda City University, Sanyo-Onoda, Japan

DOI: 10.17973/MMSJ.2026_11_2026030

e-mail: suzukish@kanto-gakuin.ac.jp

This study evaluates a positioning method using multiple hole-and-pin sets to improve assembly accuracy by decreasing "assembly shift" caused by clearance fits. While typical two hole-and-pin configurations are standard, they often introduce undesirable assembly shift due to necessary clearances. Although prior research has addressed translational assembly shift suppression, the impact of multiple sets on rotational assembly shift remains insufficiently characterized. To quantify these effects, Monte Carlo simulations were conducted, comparing configurations of n=2, 4, and 6 hole-and-pin sets arranged in a circular pattern. The simulation incorporated normal distributions for hole (Ø2.3±0.1), pin (Ø1.7 ± 0.1), and position tolerances (Ø0.2). The results demonstrate that increasing the number of sets suppresses assembly shift. Compared to the baseline requirement of n=2, the mean assembly shift size decreased by 7.8% for n=4 and 13.2% for n=6.

KEYWORDS

Tolerance analysis, Tolerance Stackup, Assembly shift, Assembly variation, Positioning, Rattling

1 INTRODUCTION

Positioning parts using hole-and-pin sets is a fundamental technique in mechanical assembly, facilitating consistent positioning accuracy independent of the operator's skill level. However, to ensure assembly efficiency and ease of insertion, a clearance fit is typically required between the pin and the hole. This clearance inevitably introduces a degree of play—often referred to as "assembly shift"—which may degrade assembly precision and introduce undesirable variations. Consequently, designers must quantitatively evaluate this assembly shift during the design phase to mitigate its impact on the final product quality. To address this requirement, various estimation methods for positioning error caused by clearance have been proposed [Drake 1999], [Gouyou 2017], [Ameta 2018] [Park 2021], and [Tang 2023].

The evaluation of assembly variation has itself been studied extensively. The methods reported in the literature can be classified into worst-case (linear stack-up) analysis, statistical analysis such as the root-sum-square and the method of moments, and numerical simulation, and surveys of this field describe the formulation of the assembly condition in the form of vector loop and matrix models [Chase 1991], [Marziale 2008]. Quantitative comparisons of these approaches have shown that the predicted assembly variation depends strongly on how the geometric tolerances are represented and on how the assembly constraints are formulated [Schleich 2016], [Ramnath 2018]., and the mathematical concepts that underlie these methods have recently been reviewed [Dantan 2024].

It should be noted that the size and position deviations of the parts in an actual assembly are distributed according to the design of the parts, the manufacturing process and the assembly process that are used, and that the assembly shift measured in a physical experiment therefore reflects the conditions of that particular experiment. Because the purpose of this study is to present the reduction rate of the assembly shift that can be expected under clearly stated and reproducible conditions, the diameters and positions of the holes and pins are specified as normal distributions with a process capability index of C_P = 1, and a position tolerance of Ø0.2 is assumed. A designer can estimate the assembly shift for his or her own production process by substituting the process capability and the tolerances of that process into the model presented in this paper.

Fig. 1 illustrates positioning methods. The positioning errors arising from such clearances have been extensively analyzed by Suzuki et al. [Suzuki 2017, 2019a, 2019b, 2020, 2022, 2025a, 2025b]. A common configuration, shown in Fig. 1(a), uses two round pins inserted into two corresponding round holes. In this setup, holes are placed at opposite ends of one component, with pins mounted at the corresponding ends of the mating part. This conventional approach the distance between the two positioning points is large relative to the overall part geometry. In applications with extreme spatial constraints, such as miniature electronic devices, maintaining an adequate distance between the holes and pins is often unfeasible, as depicted in Fig. 1(b). Under this configuration, the impact of clearance-induced assembly shift is significantly exacerbated when the assembly process and clearance between the holes and pins causes rotational assembly shift. Translational assembly shift is the same regardless of the distance between the holes and pins. The increase in variation is only seen if the parts are allowed to rotate relative to each other. As noted by Fischer [Fischer 2011], reducing the distance between positioning points causes any minute clearance at the interface to be amplified at the component's functional points due to the leverage effect (or lever ratio). Since manufacturing tolerances and assembly requirements dictate a minimum threshold for this clearance, the achievable positioning accuracy is inherently limited by the physical constraints of this specific assembly architecture.

The choice of the positioning method involves a four-way trade-off among (1) assembly feasibility, (2) the manufacturing burden of the tolerances, (3) the risk of geometric overconstraint, and (4) the reduction of the assembly shift, which is the function required of positioning. The hole-and-slot assembly [Suzuki 2017, 2019a] minimizes the risk of (3), whereas the two hole-and-pin sets shown in Fig. 1(a) involve a slightly larger risk of (3); both configurations are widely used in industry. Reducing the assembly shift further (4) requires increasing the manufacturing burden (2), and the burden of tightening the tolerance also has its limit. In this study, the risk of (3) is accepted to reduce the assembly shift (4), and the design is considered as a four-way trade-off among these items.

The assembly shift caused by the clearance between a hole and a pin is one of the principal sources of variation in the assembly of mechanical products, and it has been evaluated for various locating schemes, including the part-to-part locating of large panels by locating holes [Liu 2019] and the variation that arises in different assembly sequences [Zhu 2015]. When the clearance in a joint is combined with the deformation of the parts, the

variation is analysed by including the deformation of the joint in the model [Liu 2018].


To address these constraints, Guo et al. [Guo 2020] proposed an alternative positioning method employing multiple hole-and-pin sets, as illustrated in Fig. 1(c). This configuration leverages the inherent dimensional and positional variations of each hole-pin pair to collectively constrain the clearance, thereby enhancing assembly precision. While prior research has documented the suppression of translational assembly shift, the effectiveness of this method in mitigating rotational assembly shift remains insufficiently characterized. Consequently, the study documented in this paper uses Monte Carlo simulations to quantitatively evaluate the suppression of positioning errors, encompassing both translational and rotational components, within multiple hole-and-pin sets.

Many of the approaches to tolerance analysis reported in the literature are expected to become more sophisticated and to be implemented in three-dimensional tolerance analysis software. The aim of the present study is different: this study is intended to serve as an aid to hand calculation for practising design engineers, so that a designer can obtain a first estimate of the assembly shift while examining a design and can decide, for example, how many hole-and-pin sets to use and what tolerances to specify, before a detailed analysis is carried out with dedicated software.

2 ANALYSIS FOR ASSEMBLY SHIFT AREA BY POSITIONING USING MULTIPLE HOLE-AND-PIN SETS

Consider n sets of holes and pins arranged on a pitch circle, as illustrated in Fig. 2. The hole-part is defined as the fixed component, whereas the pin-part undergoes relative motion. A fixed coordinate system, xy, is established at the center of the pitch circle of the holes, while a movable coordinate system, XY, is centered on the pitch circle of the pins. This study accounts for variations in size and location deviations; however, form and orientation deviations are treated as zero, as they are assumed to be significantly smaller than the aforementioned factors.

The reason is as follows. For manufacturing and assembly reasons, the pins used for positioning are not made excessively long, and the holes are not made deep. The form and orientation deviations of such short pins and shallow holes are so small that their measurement itself is difficult. Form and orientation deviations would have to be taken into account if a long pin were fitted into a hole in a thick plate, which is not the case in ordinary positioning. In addition, form and orientation deviations have to be treated as parameters independent of the location deviations; in a Monte Carlo simulation, increasing the number of parameters increases the dimension of the variables generated for each trial and the number of combinations to be evaluated grows rapidly, so that introducing deviations whose effect is small is not efficient with respect to the result obtained.



(a) Ideal assembly with two hole-and-pin sets

(b) Close proximity of the hole-and-pin sets

(c) Assembly with multiple hole-and-pin sets

Figure 1. Three states of assembly using multiple hole-and-pin sets

Tab. 1 lists the variables used in this paper. Each hole and pin is assigned an index i, where i ranges from 1 to n. The diameter of the i-th hole is denoted by $D_{H,i}$, and the diameter of the i-th pin by $D_{P,i}$. The positions of the i-th hole and pin are represented by $x_{H,i}$, $y_{H,i}$ and $X_{P,i}$, $Y_{P,i}$, respectively. Variables in Tab. 1 not yet introduced will be defined in the subsequent descriptions.

Fig. 3 illustrates an assembly consisting of n=6 sets of holes and pins arranged circumferentially on a circle of radius R. In Fig. 3(a), the outlines of the parts containing the holes and pins are omitted to focus on the features themselves. At this initial state, the xy-coordinate system of the hole-part and XY-coordinate system of the pin-part coincide. The nominal centers of the holes and pins are indicated by black circles (●), while the actual centers with positional deviations are represented by plus signs (+) for holes and white circles (○) for pins. Although positional deviations exist among the six sets, no interference occurs. A design-critical point on the pin-part is defined as the "analysis point," labeled as P in the upper-right corner of the figure.

First, the difference d_i between the hole and pin diameters is defined by Equation (1):

$$d_i = D_{\mathrm{H},i} - D_{\mathrm{P},i} \tag{1}$$

In Fig. 3(b), the xy-coordinate system and the XY-coordinate system still coincide. The hole outlines are omitted. Instead, circles with diameter d_i are drawn at the center of the hole (indicated by a "+" symbol). Similarly, the pin's outlines are replaced by its center points (indicated by a "○" symbol).

Symbol	Description
x, y	Coordinate system for a hole-part (Fixed)
X, Y	Coordinate system for a pin-part (Moveable)
i	i-th hole-and-pin set (i=1,2,…,n)
n	Number of hole-and-pin sets (In this paper, n=2,4,6)
$D_{H,i}$	i-th hole diameter
$D_{P,i}$	i-th pin diameter
$x_{H,i}$, $y_{H,i}$	i-th hole position (xy-coordinate system)
$X_{P,i}$, $Y_{P,i}$	i-th pin position (XY-coordinate system)
R	Radius of a circle when the hole-and-pin sets are arranged on the circle
d_i	Difference in diameter between the i-th hole-and-pin set
Δx, Δy	Translational displacement of a pin-part
$\Delta\vartheta$	Rotational displacement of a pin-part

Table 1. Nomenclature of variables and constants




Figure 2. Assembly using multiple hole-and-pin sets

Assembly is feasible without interference if these center points lie within the circles of diameter d_i. Therefore, the assembly condition is expressed as follows:

$$\left(\frac{d_i}{2}\right)^2 \geq \left(x_{\mathrm{H},i} - X_{\mathrm{P},i}\right)^2 + \left(y_{\mathrm{H},i} - Y_{\mathrm{P},i}\right)^2 \tag{2}$$

As illustrated in Fig. 3(c), the pin-part is displaced relative to the hole-part by translational offsets Δx and Δy along the xy-axes, respectively, and by an angular displacement $\Delta\vartheta$ The assembly feasibility—specifically, the presence of interference—is determined by evaluating whether the centers of the pins (indicated by the "○" symbol) lie within circles of diameter d_i. Given the translational displacements Δx and Δy and the rotational displacement $\Delta\vartheta$ at the pin center ($X_{\mathrm{P},i}$, $Y_{\mathrm{P},i}$), the resulting position of the hole in the xy-coordinate system is expressed as follows:

$$x_{\mathrm{P},i} = X_{\mathrm{P},i}\cos\Delta\theta - Y_{\mathrm{P},i}\sin\Delta\theta + \Delta x \tag{3}$$

$$y_{\mathrm{P},i} = X_{\mathrm{P},i}\sin\Delta\theta + Y_{\mathrm{P},i}\cos\Delta\theta + \Delta y \tag{4}$$


By replacing $X_{\mathrm{P},i}$ and $Y_{\mathrm{P},i}$ in equation (2) with $x_{\mathrm{P},i}$ and $y_{\mathrm{P},i}$ in equations (3) and (4), the assembly condition for the two parts is derived as shown in Equation (5).

$$\left(\frac{d_i}{2}\right)^2 \geq \left(x_{\mathrm{H},i} - x_{\mathrm{P},i}\right)^2 + \left(y_{\mathrm{H},i} - y_{\mathrm{P},i}\right)^2 \tag{5}$$


When displacements Δx, Δy, and $\Delta\vartheta$ occur at the pin-part, a point P(X, Y) at the analysis point shifts to P′. In the fixed xy-coordinate system, the coordinates of the position of P′ are expressed as follows:

$$x_{\mathrm{P}'} = X\cos\Delta\theta - Y\sin\Delta\theta + \Delta x \tag{6}$$


$$y_{\mathrm{P}'} = X\sin\Delta\theta + Y\cos\Delta\theta + \Delta y \tag{7}$$



(a) Fitting holes and pins



(b) Diameters differences d_i and center points of the pins



(c) After translation and rotation

Figure 3. Assembly condition of hole-and-pin sets

For instance, by setting R=10, X=30, and Y=10, and varying Δx, Δy, and $\Delta\vartheta$, the resulting plots for point P' are shown in Fig. 4. Fig. 4(a), (b), and (c) each feature a distinct number and size of hole-and-pin sets. This distribution of points is defined as the "assembly shift area" in this paper. This area represents the potential range of the analysis point caused by the assembly shift, enabling an estimation of the degradation in positioning accuracy. In subsequent sections, the assembly shift area is quantitatively evaluated based on the dimension of its bounding rectangle.

3 EXPERIMENTAL APPROACH TO ASSEMBLY SHIFT AREA GENERATION BASED ON MONTE CARLO SIMULATION

3.1 Simulation conditions

In this section, Monte Carlo simulations were conducted to evaluate the effect of multiple hole-and-pin sets on positioning accuracy under the conditions summarized in Tab. 2. The number of simulation trials was set to N=10000. The number of hole-and-pin sets, n, varied as n=2,4, or 6. While n=2 represents the most common two hole-and-pin sets positioning, n=4 and n=6 were included to analyze the impact of increasing the sets; n=6 was defined as the practical limit considering economic and manufacturing feasibility.

The Monte Carlo method has been applied widely to the tolerance analysis of mechanical assemblies, including the case in which geometric tolerances are taken into account [Yan 2015]. In the present study, this method is applied to the assembly condition of Equation (5), which represents the condition for the insertion of the pins into the holes.


Fig. 5 illustrates the specifications for the hole-part and the pin-part. As shown in Fig. 5(a) and Tab. 2, the i-th hole diameter $D_{H,i}$ is specified as 2.3 ± 0.1, resulting in a maximum material size (MMS) of 2.2. Similarly, as shown in Fig. 5(b) and Tab. 2, the i-th pin diameter $D_{P,i}$ is specified as 1.7 ± 0.1, resulting in an MMS of 1.8. It is assumed that these diameters are manufactured using processes that yield normal distributions with C_P=1. As depicted in Fig. 5(a) and 5(b), the holes and pins are arranged at equal intervals on a pitch circle with a radius of R=10. Fig. 5(c) and 5(d) show the hole arrangements for n=4 and n=2, respectively. Since the pin arrangements for n=4 and n=2 follow the same spatial distribution as the holes, their corresponding figures have been omitted.

In addition to these specifications, Ø0.2 position tolerances relative to matching datum systems were specified for the holes and pins. Had the maximum material requirement (MMR) been applied, the maximum material virtual size (MMVS) for both the holes and pins would be 2, theoretically allowing for assembly with zero clearance even in the worst-case scenario. However, the application of MMR would result in the relaxation of geometric tolerances depending on the sizes of the holes and pins, thereby complicating the analysis. Consequently, MMR was not applied in this experiment. In the simulation, the diameters and positions of the holes and pins were generated using independent random variables. Furthermore, form and orientation deviations were assumed to be negligible and were treated collectively as location deviations.


The analysis point was set at X=30,Y=0, corresponding to three times the pitch circle radius R, as specified in the eighth row of Tab. 2 and Fig. 5(a). This configuration enables the verification of the suppression effects on both translational and rotational assembly shifts.

As shown in rows 9 and 10 of Tab. 2, the hole component was fixed while the pin-part was translated within the ranges of Δx=0.05j (j=0,±1,…,±10) and Δy=0.05k (k=0,±1,…,±10). Specifically, the pin was translated from the nominal position (Δx=0, Δy=0) by a maximum of ±0.5 mm in increments of 0.05 mm. For each of these 21×21=441 translational combinations, the part was rotated within the range of $\Delta\vartheta$=0.04l° (l=0,±1,…,±60), corresponding to a maximum deviation of $\Delta\vartheta$=±2.4° from the design orientation $\Delta\vartheta$=0 in 0.04° increments. With 121 angular variations, a total of 53361 assembly trials (21×21×121) were performed. The feasibility of each assembly was evaluated using Equation (5). The resulting analysis points were plotted for cases where assembly was successful, as shown in Fig. 4.


For each trial, Equation (5) was evaluated for each combination of the translational displacements (Δx, Δy) and the rotational displacement $\Delta\vartheta$ of the pin part; the configurations satisfying Equation (5) for all n hole-and-pin sets simultaneously were regarded as assembleable, and the assembly shift size of the trial was defined as the range of the Y-coordinate of the analysis point (X, Y) = (30, 0) over the assembleable configurations. The translational and rotational steps (0.05 mm and 0.04°) were selected by refining them until the worst-case assembly shift size, known analytically from the rattling-area theory [Suzuki 2019b, Suzuki 2022] (2.400 mm for n = 2, Tab. 6(a), with the largest hole Ø2.4 and the smallest pin Ø1.6), was well reproduced; the selected steps reproduce it with an error of 0.5% (0.013 mm).



(a) Two hole-and-pin sets (Worst-case)




(b) Two hole-and-pin sets (Nominal feature)




(c) Six hole-and-pin sets (Random size and position)

Figure 4. Examples of assembly shift areas by plotted points



(a) Specifications for six-hole part

(b) Specifications for six-pin part




(c) Specifications for four-hole part

(d) Specifications for two-hole part

Figure 5. Specifications for Monte Carlo simulation

Item	Conditions	Unit
Number of simulation trials	N=10000	-
Number of multiple hole-and-pin sets	n=2,4,6	-
i-th hole diameter	$D_{H,i}$=2.3±0.1 (Normal distribution, C_P=1)	mm
i-th pin diameter	$D_{P,i}$=1.7±0.1 (Normal distribution, C_P=1)	mm
Pitch circle radius	R=10	mm
i-th hole position (xy-coordinate system)	$x_{H,i} = R \cos \varphi$ $y_{H,i} = R \sin \varphi$ Position tolerance 0.2 (Normal distribution, C_P=1) For n=2, φ takes the values of 0° and 180° For n=4, φ takes the values of 0°,90°,180° and 270° For n=6, φ takes the values of 0°,60°,120°,180°,240° and 300°	mm
i-th pin position (XY-coordinate system)	$X_{P,i} = R \cos \varphi$ $Y_{P,i} = R \sin \varphi$ Position tolerance 0.2 (Normally distribution, C_P=1) For n=2, φ takes the values of 0° and 180° For n=4, φ takes the values of 0°,90°,180° and 270° For n=6, φ takes the values of 0°,60°,120°,180°,240° and 300°	mm
Analysis point	X=30, Y=0	mm
Translation displacement for pin-part	Δx=0.05j (j=0,±1, … , ±10) Δy=0.05k (k=0,±1, … , ±10)	mm
Rotation displacement for pin-part	$\Delta\theta$=0.04l (l=0,±1, … , ±60)	deg

Table 2. Experimental conditions



(a) Diameter of Hole (1) Mean:2.300, St.dev:0.033

(b) Diameter of Pin (1) Mean:1.700, St.dev:0.033

(c) X-position of Hole (1) Mean:10.000, St.dev:0.033

(d) Y-position of Hole (1) Mean:0.000, St.dev:0.033

Figure 6. Examples of the distributions of generated random numbers

3.2 *Randomized modeling of diameter and positional variations for holes and pins*

Under the conditions specified in Tab. 2, random numbers were generated for the diameters and positions of the holes and pins. These variables were modeled as normally distributed with a process capability index of C_P=1. The stochastic data were generated using Apogee (version 4.13.2.15077; Statistical Design Institute, LLC). A representative histogram of the resulting distributions is provided in Fig. 6. Because Fig. 6 depicts only a sample distribution, the statistical properties—specifically the mean, standard deviation, skewness, and kurtosis—for all holes and pins are detailed in Tab. 3 (n=2), Tab. 4 (n=4), and Tab. 5 (n=6). To ensure consistency across the simulation, the data for holes and pins i=1 and i=2 in Tab. 4 were sourced from Tab. 3; this allows for a direct comparison when simulating the increase in the number of pins from two to four. Similarly, the data for i=1 and i=2 in Tab. 5 were also sourced from Tab. 3. Note that for n=6 (Tab. 5), the data for i=3 and i=4 from Tab. 4 were not utilized, as the spatial arrangement of the holes and pins differs between the n=4 and n=6 configurations.

The results in Tab. 3, 4, and 5 show that the average diameter of the holes and pins matches the nominal size to within 1 µm, and the average positions of the holes and pins also match the theoretically exact positions within 1 µm. In addition, the standard deviation was 0.033, the skewness was close to 0, and the kurtosis was close to 3, all of which were close enough to the design values, confirming that the data obtained was sufficient for the experiment.

The diameters and the positions of the holes and pins were assumed to be independent and normally distributed with a process capability index of C_P = 1. This is an example of a general

and typical assumption; the distribution parameters, such as the process capability index, the type of the distribution and the tolerance values, can be set by the reader according to the capability of his or her own manufacturing process, and the assembly shift under those conditions can be evaluated with the model presented in this paper. The reduction rate reported in this paper is the value expected under the assumption stated above.

The number of trials was determined from the convergence of the computed assembly shift size using three criteria. First, for the mean, the relative change in the estimated value is less than 1%. Second, the standard errors of the standard deviation, the skewness and the kurtosis decrease by the theoretical factor of $\sqrt{10}$ = 3.16, the deviation from the theoretical value being within 10%. Third, the number of trials required to keep the half-width of the 95% confidence interval within ±0.1 is obtained from the asymptotic expressions for the standard errors. For n = 2, the 95% confidence half-width of the mean is 1.27% of the mean at N = 100 and 0.12% at N = 10,000, and the mean itself is stable to within 0.05% from N = 1,000 onwards. The standard errors of the standard deviation, the skewness and the kurtosis decreased by factors of 3.12 to 3.21 between N = 1,000 and N = 10,000, within 1.5% of the theoretical factor of $\sqrt{10}$ = 3.16. Of the four statistics, this number of trials N is largest for the kurtosis: the condition $1.96 \cdot \sqrt{24/N} \leq 0.1$ requires $N \geq 9{,}220$. N = 10,000 was therefore adopted, which satisfies the criteria for all four statistics reported in this paper.

3.3 *Assembly shift area simulation using multiple hole-and-pin sets*

Fig. 7 illustrates the graphical user interface (GUI) of a Windows application developed in Visual Studio 2022, which implements the theoretical framework described in Section 2.

Fig. 8 illustrates an application example where the translational assembly shift area for a specific analysis point at X=30,Y=0 is plotted. The central circle depicted in Fig. 8(a) through 8(d) represent the worst-case translational assembly shift area. Its radius, denoted as δ_{WC}, is derived from the specifications provided in Fig. 5. This value is calculated by considering the maximum hole size (adding the upper limit deviation of 0.1 to the nominal size of 2.3) and the minimum pin size (subtracting the lower limit deviation of 0.1 from the nominal size of 1.7), as follows:

$$\delta_{WC} = \frac{(2.3 + 0.1) - (1.7 - 0.1)}{2} = 0.4 \tag{8}$$

Furthermore, the ellipses centered in Fig. 8(a) to 8(d) represent the worst-case rotational assembly shift area. Based on the Reference, Suzuki et al. (2019), the magnitude of this range along the Y-axis is calculated using Equation (9).

i	Hole /Pin	Diameter /Position		Mean	Standard Deviation	Skewness	Kurtosis
1	Hole	Diameter		2.30000	0.0333	0.002	2.958
		Position	X	10.00000	0.0333	-0.002	2.985
			Y	0.00000	0.0333	0.001	3.000
	Pin	Diameter		1.70000	0.0333	-0.004	2.970
		Position	X	10.00000	0.0333	0.003	3.019
			Y	0.00000	0.0333	-0.003	2.982
2	Hole	Diameter		2.29999	0.0333	-0.006	2.998
		Position	X	-10.00001	0.0333	-0.006	2.982
			Y	0.00000	0.0333	0.001	2.977
	Pin	Diameter		1.69999	0.0333	-0.012	3.014
		Position	X	-9.99999	0.0333	0.009	2.976
			Y	0.00000	0.0334	-0.001	3.041

Table 3. Results of Monte Carlo simulation (n=2)

i	Hole /Pin	Diameter /Position		Mean	Standard Deviation	Skewness	Kurtosis
1	Hole	Diameter		Sourced from Table 3.			
		Position	X,Y				
	Pin	Diameter					
		Position	X,Y				
2	Hole	Diameter					
		Position	X,Y				
	Pin	Diameter					
		Position	X,Y				
3	Hole	Diameter		2.30001	0.0333	0.009	2.996
		Position	X	0.00000	0.0333	-0.001	2.996
			Y	10.00000	0.0333	-0.003	3.016
	Pin	Diameter		1.70000	0.0333	-0.003	2.998
		Position	X	0.00000	0.0333	0.002	2.994
			Y	10.00000	0.0334	0.000	3.023
4	Hole	Diameter		2.29999	0.0334	-0.016	3.044
		Position	X	0.00000	0.0333	-0.002	3.003
			Y	-10.00001	0.0334	-0.005	3.029
	Pin	Diameter		1.70001	0.0333	0.008	3.011
		Position	X	0.00001	0.0333	0.007	2.966
			Y	-9.99999	0.0334	0.006	3.023

Table 4. Results of Monte Carlo simulation (n=4)

$$y_{WC} = 2\delta_{WC}\left(\frac{2X}{L} - 1\right) = 2 \times 0.4\left\{\frac{2 \times (30 + 10)}{20} - 1\right\} = 2.4 \tag{9}$$

Note that a constant of 10 mm is added to the X-coordinate in this formula to account for an offset in the coordinate origin between the reference model and the current simulation.

Fig. 8(a) illustrates the assembly of two hole-and-pin sets at the least material size (LMS) with zero orientation and location deviation, with both patterns centered on one another, which results in the maximum possible assembly shift. The simulation results demonstrate that the plotted points align precisely within the theoretical boundaries of both the translational and rotational assembly shift areas, thereby validating the proposed numerical model. Fig. 8(b) shows a sample in which random numbers were assigned to the diameters and positions of two hole-and-pin sets. Compared to Fig. 8(a), the assembly shift area is narrower because the diameter and position of the holes and pins were allowed to deviate within their specified tolerances from the conditions represented in Fig. 8(a). Using the size of the assembly shift area in the Y-axis direction, y_{2p}, as an index for comparison, y_{2p} =1.85, which is smaller than y_{WC} =2.4 in the worst-case case of Fig. 8(a). The size of the assembly shift area in the Y-axis direction is hereafter defined as the "assembly shift size." Fig. 8(c) shows one of a sample in which random numbers were assigned to the diameters and positions of four hole-and-pin sets. Compared to Fig. 8(b), the assembly shift area is narrower, however the assembly shift size, y_{4p}, is only slightly smaller than y_{2p}, and there is no significant difference. Fig. 8(d)

shows one of a sample in which random numbers were assigned to the diameters and positions of a sample of six hole-and-pin sets. Compared to Fig. 8(c), the plotted area is even narrower, and the assembly shift size, y_{6p}, is smaller than y_{4p}. These samples demonstrate that an increased number of hole-and-pin sets suppresses the assembly shift.

The numerical model was verified by comparing the simulation results with the closed-form solutions. Fig. 8(a) shows the case in which the hole-and-pin sets are at their least material size and have no size or location deviation, which corresponds to the maximum possible assembly shift. The plotted points are contained within the circle of radius δWC given by Equation (8) and within the ellipse given by Equation (9), which is derived from the analytical model of Suzuki et al. [Suzuki 2019a]. This agreement confirms that the assembly condition of Equation (5) and the simulation procedure reproduce the theoretical assembly shift area for both the translational and the rotational components.

Accordingly, we conducted 10,000 Monte Carlo simulations using the assembly shift size as an evaluation metric, and the comparison results are shown in Tab. 6. Tab. 6 is divided into four sections: (a), (b), (c), and (d). In section (a), the first to third rows each show the assembly shift size under the design conditions. The value in each row remains the same, regardless of the number n of hole-and-pin sets in section (a), because the positions of the holes and pins in section(a) are calculated using the nominal positions, which do not include any deviations. The first row shows the assembly shift size under worst case (WC). The second row shows the assembly shift size, determined by the clearance between holes and pins at their nominal size. The third row shows the assembly shift size occurring when holes and pins are at their maximum material size (MMS). The worst case assembly shift size for the first row is determined to be y_{WC} =2.4 based on Equation (9). For the second row, the assembly shift size under the nominal hole and pin sizes is calculated as follows:

$$\delta_{\mathrm{Nom}} = \frac{2.3 - 1.7}{2} = 0.3 \tag{10}$$

$$y_{\mathrm{Nom}} = 2\delta_{\mathrm{Nom}}\left(\frac{2X}{L} - 1\right) = 2 \times 0.3\left\{\frac{2 \times (30 + 10)}{20} - 1\right\} = 1.8 \tag{11}$$

Similarly, the assembly shift size for the third row, assuming the holes and pins are at their maximum material size (MMS), is calculated as follows:

$$\delta_{\mathrm{MMS}} = \frac{(2.3 - 0.1) - (1.7 + 0.1)}{2} = 0.2 \tag{12}$$

$$y_{\mathrm{MMS}} = 2\delta_{\mathrm{MMS}}\left(\frac{2X}{L} - 1\right) = 2 \times 0.2\left\{\frac{2 \times (30 + 10)}{20} - 1\right\} = 1.8 \tag{13}$$

The fourth row contains the difference y_{WC} - y_{MMS} between the worst case (WC) (first row) and the MMS (third row).

Section (b) of Tab. 6 presents the maximum (1st row), mean (2nd row), minimum (3rd row), range between the maximum and minimum (4th row), and standard deviation (5th row) of the assembly shift size. These experimental values were obtained through Monte Carlo simulations for each number of hole-and-pin sets (n=2, 4, 6). The data in sections (a) and (b) are also visually represented in Fig. 9, where the horizontal axis indicates the number of hole-and-pin sets n and the vertical axis indicates the assembly shift size.

In all the Monte Carlo simulations, every trial yielded at least one configuration satisfying Equation (5) for all n hole-and-pin sets simultaneously; that is, no trial had to be excluded because of interference. This is because the design tolerance keeps the clearance non-negative even in the worst case, whereas interference would require several of the size and position deviations to reach their worst-case values simultaneously; with C_P = 1, a single deviation exceeds the tolerance band (±3σ) with a probability of only 0.27%, and the probability of such a simultaneous occurrence is negligibly small.

i	Hole /Pin	Diameter /Position		Mean	Standard Deviation	Skewness	Kurtosis
1	Hole	Diameter		Sourced from Table 3.			
		Position	X,Y				
	Pin	Diameter					
		Position	X,Y				
2	Hole	Diameter					
		Position	X,Y				
	Pin	Diameter					
		Position	X,Y				
3	Hole	Diameter		Sourced from Table 4.			
		Position	X	4.99999	0.0333	-0.007	2.977
			Y	8.66025	0.0333	0.000	3.007
	Pin	Diameter		Sourced from Table 4.			
		Position	X	5.00000	0.0333	0.003	2.994
			Y	8.66024	0.0334	-0.012	3.047
4	Hole	Diameter		Sourced from Table 4.			
		Position	X	-5.00001	0.0333	-0.009	2.998
			Y	8.66025	0.0333	-0.001	3.000
	Pin	Diameter		Sourced from Table 4.			
		Position	X	-5.00001	0.0333	-0.007	2.966
			Y	8.66025	0.0333	-0.005	3.009
5	Hole	Diameter		2.30000	0.0334	-0.001	3.031
		Position	X	-5.00000	0.0334	0.005	3.087
			Y	-8.66026	0.0333	-0.002	3.003
	Pin	Diameter		1.70001	0.0333	0.006	3.002
		Position	X	-4.99999	0.0333	0.008	2.998
			Y	-8.66025	0.0333	0.007	2.990
6	Hole	Diameter		2.30000	0.0333	0.003	2.997
		Position	X	4.99999	0.0333	-0.005	2.994
			Y	-8.66025	0.0333	0.006	3.001
	Pin	Diameter		1.70000	0.0334	0.000	3.018
		Position	X	5.00000	0.0334	-0.002	3.022
			Y	-8.66026	0.0333	-0.004	3.005

Table 5. Results of Monte Carlo simulation (n=6)

		Number of hole-and-pin sets		
		n=2	n=4	n=6
(a) Design condition (mm)	1. Worst case (WC)	2.400	2.400	2.400
	2. Nominal size	1.800	1.800	1.800
	3. Maximum material size	1.200	1.200	1.200
	4. Worst case - MMS	1.200	1.200	1.200
(b) Experimental values (mm)	1. Maximum value	2.123	1.935	1.788
	2. Mean value	1.707	1.575	1.482
	3. Minimum value	1.290	1.076	1.001
	4. Range (max - min)	0.833	0.858	0.788
	5. Standard deviation	0.109	0.106	0.103
(c) Decrease rate of (b) relative to (a)	1. Maximum value	11.5%	19.4%	25.5%
	2. Mean value	5.1%	12.5%	17.7%
	3. Minimum value	-7.5%	10.3%	16.6%
	4. (WC-MMS) vs (max-min)	30.6%	28.5%	34.4%
(d) Decrease rate of (b) relative to n=2	1. Maximum value	-	8.9%	15.8%
	2. Mean value	-	7.8%	13.2%
	3. Minimum value	-	16.6%	22.5%

Table 6. Effect of multiple hole-and-pin sets on assembly shift size




Figure 7. Example of application software that plots an assembly shift area




Figure 8. Assembly shift area samples at position X=30, Y=0 (Unit: mm)

Section (c) of Tab. 6 presents the decrease rate in the experimental values shown in section (b) relative to the design condition values in section (a). For instance, the 11.5% decrease for the maximum value at *n*=2 (1st row, section (c)) represents the reduction from the "Worst case" value of 2.400 in section (a) to the maximum value of 2.123 in section (b). The percentage decrease, $\Delta_{(c)}$, is calculated as follows:

$$\Delta_{(c)} = \frac{2.4 - 2.123}{2.400} \times 100 = 11.5\% \quad (14)$$

Using a similar calculation method, the decrease rate is 19.4% for *n*=4 hole-and-pin sets and 25.5% for n=6. As illustrated in Fig. 9, the maximum value of 1.788 for n=6 is equivalent to an assembly shift of 1.8 at the nominal size, indicating that the assembly shift has been effectively suppressed to this level. These results demonstrate that under specific assembly conditions, it is unnecessary to account for the worst-case assembly shift. Furthermore, increasing the number of hole-and-pin sets allows for a further reduction in the anticipated assembly shift.

It should be noted, however, that the benefit of increasing *n* saturates: the reduction of the mean assembly shift size relative to *n* = 2 is 7.6% for *n* = 4 and 13.2% for *n* = 6, whereas the number of holes and pins to be machined increases in proportion to *n*. Moreover, a configuration must satisfy Equation (5) for all n sets simultaneously, so the region of assembleable configurations shrinks as n increases, which increases the risk of interference in the worst-case combinations. In this study, *n* = 6 was therefore set as the practical limit considering economic and manufacturing feasibility.

The mean value for *n*=2 in the second row of Tab. 6(c) shows a decrease rate of 5.1%. This value represents the decrease rate from the nominal size of 1.800 (Section (a), 2nd row) to the experimental mean value of 1.707 (Section (b), 2nd row). The decrease rate, δ, is calculated similar to Equation (11). Here, the decrease rate is 5.1%, although not as significant as the decrease rate in the worst case and the maximum value (2nd row). As the number of hole-and-pin sets increases to *n*=4 and *n*=6, the decrease rates rise to 12.5% and 17.7%, respectively. This trend confirms that the assembly shift size decreases in proportion to the number of hole-and-pin sets.

Furthermore, considering the minimum value for *n*=2 in the third row of Tab. 6(c), the value of -7.5% represents the decrease rate from the maximum material size of 1.200 (section (a), 3rd row) to the experimental minimum value of 1.290 (section (b), 3rd row). Notably, this is the only negative value in Tab. 6(c). The diameters of the holes and pins were examined when a minimum value of 1.290 was obtained from 10,000 samples. The hole diameters are Ø2.2242 and Ø2.2667, which are within the tolerances, however the diameters of the two holes are larger than MMS(=2.2). Similarly, the pin diameters are Ø1.7899 and Ø1.7008, which are also within the tolerances, however the diameters of the two pins are smaller than MMS(=1.8). Thus, combinations where both the holes and pins simultaneously meet or are close to MMS rarely occur in approximately 10,000 Monte Carlo simulations. Therefore, the minimum value is slightly larger than the maximum material size value of 1.200, which yields a negative value for the decrease rate. When the number of hole-and-pin sets increases to *n*=4, the decrease rate is 10.3%, and when it increases to *n*=6, the decrease rate is 16.6%. In these cases, because the number of hole-and-pin sets has increased, it was confirmed that the positional deviation of the holes and pins can result in a smaller assembly shift size than the theoretical assembly shift size y_{MMS} = 1.2 for *n*=2 at MMS.

In Tab. 6, section (c), for *n*=2 (the 4th row), the "Maximum value – Minimum value" of 0.833 in section (b), for *n*=2 (the 4th row) represents a 30.6% decrease rate compared to the "Worst case–MMS" value of 1.200 in section (a). Following the same calculation method, the decrease rates for *n*=4 and *n*=6 are 28.5% and 34.4%, respectively. These results indicate that not only is the absolute assembly shift size reduced—as observed in the first through third rows of section (c)—but the variation in assembly shift size is also suppressed. This suppression of variability may contribute significantly to the enhancement of product quality.

Section (d) of Tab. 6 compares the experimental values for *n*=4 and *n*=6 relative to the *n*=2 shown in section (b). For instance, the 8.9% value in the first row of section (d) represents the decrease rate in the maximum value for *n*=4 (1.935) compared to the value for *n*=2 (2.123) in section (b). The decrease rate $\Delta_{(d)}$ is calculated as follows:

$$\Delta_{(d)} = \frac{2.123 - 1.935}{2.123} \times 100 = 8.9\% \quad (15)$$

The other decrease rates in section (d) are calculated using a similar procedure. Across the maximum value, mean value, and minimum value, section (d) demonstrates that the assembly shift size decreases as the number of hole-and-pin sets increases. The tolerance and the process capability index C_P affect the assembly shift size through the standard deviation $\boldsymbol{\sigma = t/3C_P}$ of the deviations. The design tolerance of ±0.10 mm (C_P = 1) adopted in this study corresponds to the assembly limit at which the clearance vanishes in the worst case; a larger tolerance is not admissible because the worst-case assembly would no longer be feasible. A tighter tolerance, i.e., a smaller σ, reduces the size and position variations; in the proposed method, however, these variations are turned to advantage and used to suppress the assembly shift, so that a smaller σ does not reduce the assembly shift size but rather increases it. The assembly shift size is therefore minimized, within the range in which assembly remains feasible, by the largest admissible σ, the upper bound of which is the design tolerance of ±0.10 mm at C_P = 1. The dependence on the pitch circle radius R, in turn, follows directly from the rattling-area theory: at the analysis point the assembly shift is proportional to the lever ratio *X*/*R*, and the analysis point of this study (*X* = 3*R*) fulfills the positioning function under this proportional relationship.




Figure 9. Effect of multiple hole-and-pin sets on assembly shift size

4 CONCLUSION

This study demonstrated that increasing the number of positioning hole-and-pin sets suppresses assembly shift, specifically accounting for variation in hole and pin sizes and positions.

The experimental conditions were simulated using a Monte Carlo simulation with 10,000 trials. The number of hole-and-pin sets was set to *n*=2,4 and 6. The diameter of each hole was Ø2.3±0.1 (normal distribution, C_p =1), and the diameter of each pin was Ø1.7 ± 0.1 (normal distribution, C_p=1). The sets were arranged in a circular pattern with equal angular spacing at a radius of *R*=10, with a position tolerance of Ø0.2. The analysis point was located 30mm from the center of this arrangement. Using the size of the assembly shift area in the longitudinal direction (Y-direction) as the primary indicator, the simulation demonstrated that the decrease rate (mean value) of assembly shift size was 7.8% for *n*=4 and 13.2% for *n*=6, compared to the minimum requirement for assembly of *n*=2.

These results demonstrate that increasing the number of hole-and-pin sets can effectively reduce rotational assembly shift—without the need for stricter size tolerances. Designers can balance the trade-off between increasing the number of hole-and-pin sets and tightening tolerances. By simultaneously designing the mechanism and its tolerances, they can enhance product quality more efficiently without incurring additional costs.

Finally, the limitations of the proposed model should be noted: the size and position deviations of the holes and pins are assumed to be independent and normally distributed, and the form and orientation deviations are treated as negligible; the reported reduction rates are valid under these conditions. In an actual process, the mean may shift due to wear of the die and the distribution may split into multiple peaks when parts are supplied by multiple suppliers, in which case the individual deviations and their distributions must be determined when applying the model to a real process.

ACKNOWLEDGMENTS

The authors would like to thank Mr. Bryan Fischer for his professional English editing and helpful comments on the manuscript.

REFERENCES

[Ameta 2018] Ameta, G., Singh, G., Davidson, J. K., and Shah. J. J. Tolerance-Maps to Model Composite Positional Tolerancing for Patterns of Features. Journal of Computing and Information Science in Engineering, June 2018, Vol.18, No.3., pp 031003-031011.

[Chase 1991] Chase, K. W., and Parkinson, A. R. A Survey of Research in the Application of Tolerance Analysis to the Design of Mechanical Assemblies. Research in Engineering Design, 1991, Vol.3, No.1., pp 23-37.

[Dantan 2024] Dantan, J.-Y., and Homri, L. Overview of Mathematical Concepts for Tolerance Analysis. Procedia CIRP, 2024, Vol.129, pp 73-78.

[Drake 1999] Drake, P. Dimensioning and Tolerancing Handbook. New York: McGraw-Hill, 1999. ISBN 978-0070181311

[Fischer 2011] Fischer, B. R. Fischer, B. R. Mechanical Tolerance Stackup and Analysis (2nd ed.). New York: CRC Press, 2011. ISBN 978-1439815724

[Gouyou 2017] Gouyou, D., Ledoux, Y., Teissandier, D., and Delos, V. Tolerance analysis of overconstrained and flexible assemblies by polytopes and finite element computations: application to a flange. Research in Engineering Design, April 2017, Vol.29, pp 55-66.

[Guo 2020] Guo, H., Zhang, Z., Liu, H., Xiao, M., and Jin, X. A Solution to the Accuracy of Multi-Pin Positioning Based on Optimization. IEEE Access, December 2020, Vol.9, pp 2443-2453.

[Liu 2018] Liu, T., Li, Z.-M., Jin, S., and Chen, W. A Variation Analysis Method for Linkage Mechanism with Consideration of Joint Clearance and Deformation. International Journal of Precision Engineering and Manufacturing, October 2018, Vol.19, No.10., pp 1495-1506.

[Liu 2019] Liu, X., An, L., Wang, Z., Tan, C., Wang, X., and Yu, S. Assembly Variation Analysis of Aircraft Panels under Part-to-Part Locating Scheme. International Journal of Aerospace Engineering, 2019, Vol.2019, Article ID 9563596, pp 1-15.

[Marziale 2008] Marziale, M., and Polini, W. A Review of Two Models for Tolerance Analysis of an Assembly: Vector Loop and Matrix. International Journal of Advanced Manufacturing Technology, 2008, Vol.43, No.11-12., pp 1106-1123.

[Park 2021] Park, J. W., Park, J., Kim, H., Kim, N., and Kim, D. Y. Assembly Part Positioning on Transformable Pin Array Fixture by Active Pin Maximization and Joining Point Alignment. IEEE Transactions on Automation Science and Engineering, January 2021, Vol.19, No.2., pp 1047-1057.

[Ramnath 2018] Ramnath, S., Haghighi, P., Chitale, A., Davidson, J. K., and Shah, J. J. Comparative Study of Tolerance Analysis Methods Applied to a Complex Assembly. Procedia CIRP, 2018, Vol.75, pp 208-213.

[Schleich 2016] Schleich, B., and Wartzack, S. A Quantitative Comparison of Tolerance Analysis Approaches for Rigid Mechanical Assemblies. Procedia CIRP, 2016, Vol.43, pp 172-177.

[Suzuki 2017] Suzuki, S. and Wakayama, N. Analysis of Assembly Variation by Positioning Between Two Parts using a Hole and a Slot. Journal of Japan Society for Design Engineering, September 2017, Vol.52, No.9., pp 553-566.

[Suzuki 2019a] Suzuki, S. and Wakayama, N. Analysis of Assembly Variation by Positioning Between Two Parts using a Hole and a Slot. Journal of Japan Society for Design Engineering, October 2019, Vol.54, No.10., pp 681-696.

[Suzuki 2019b] Suzuki, S., and Kanada, T. Analysis of Assembly Variation Between Two Parts Constrained Using Hole and Boss Features. Journal of Japan Society for Design Engineering, July 2019, Vol.54, No.7., pp 457-472.

[Suzuki 2020] Suzuki, S., and Kanada, T. Theoretical Analysis of Assembly Variation by Positioning between Two Parts using a Round Pin and a Diamond Pin. Procedia CIRP, 2020, Vol.92, pp 75-80.

[Suzuki 2022] Suzuki, S., and Kanada, T. Analysis of Assembly Variation between Two Parts Constrained using Hole and Boss Features (2nd Report, Derivation of the Diameter of the Circle Circumscribing the Rattling Area). Journal of Japan Society for Design Engineering, December 2022, Vol.57, No.12., pp 607-620.

[Suzuki 2025a] Suzuki, S., Otsuka, A., Kawaguchi, Y., and Kanada, T. Analysis of Assembly Variation by Positioning Between Two Parts using a Hole and a Slot (2nd Report, Derivation of the Radius of Circle Circumscribing the Rattling Area). Journal of Japan Society for Design Engineering, January 2025, Vol.60, No.1., pp 27-38.

[Suzuki 2025b] Suzuki, S., Otsuka, A., Kawaguchi, Y., and Kanada, T. Analysis of Assembly Variation between Two Parts Constrained using Hole and Boss Features (3rd Report, Rattling Area in Case of Location Deviation Occurs in the Distance between Two Bosses). Journal of Japan Society for Design Engineering, September 2025, Vol.60, No.9., pp 487-502.

[Tang 2023] Tang, L., and Xu, X. Study on the Calculation of Hole/Pin Floating Deviation for "Two Pins on One Side". Journal of Physics: Conference Series, 2023, 2578, 012030.

[Yan 2015] Yan, H., Wu, X., and Yang, J. Application of Monte Carlo Method in Tolerance Analysis. Procedia CIRP, 2015, Vol.27, pp 281-285.

[Zhu 2015] Zhu, Z., and Qiao, L. Analysis and Control of Assembly Precision in Different Assembly Sequences. Procedia CIRP, 2015, Vol.27, pp 117-123.

CONTACTS:

Associate Professor, Shinya Suzuki, PhD.
College of Science and Engineering,
Advanced Mechanical Engineering Course
Kanto Gakuin University
1-50-1 Mutsuura-higashi, Kanazawa-ku, Yokohama
236-8501 JAPAN, +81-45-786-8712
suzukish@kanto-gakuin.ac.jp

LICENSE CREATIVE COMMONS:

The article is published under the terms and conditions of the Creative Commons Attribution 4.0 International License (CC BY 4.0).